



Item description

The WAGO USB Communication Cable connects a PC (notebook) to both the service interface of the 857 Series Signal Conditioners and the configuration interface of WAGO's I/O fieldbus couplers/controllers.

Notice!

Using the WAGO 759-923 USB Communication Cable

in combination with select programmable fieldbus controllers

Subject to changes. Please also observe the further product documentation!

requires the specific firmware versions listed below:

750-841: Firmware Version 12 (or higher)

750-872/0020-0000: Firmware Version 2 (or higher)

Data

Technical data

Connection type	4-pole male connector - USB A-type plug
Pole number	4
Cable length	5 m
Supported operating systems	Windows XP (SP3 or higher) Windows 7 Windows 10

Physical data

Width	15 mm / 0.591 inches
Height	50 mm / 1.97 inches
Depth	19 mm / 0.748 inches

Mechanical data

Weight	114.3 g
--------	---------

Environmental requirements

Ambient temperature (operation)	-25 ... +70 °C
Protection type	IP20
EMC immunity to interference	per EN 61000-4-3, EN 61000-4-6
EMC emission of interference	per EN 55022
Fire load	0.132 MJ

Commercial data

Product Group	15 (Remote I/O)
eCl@ss 10.0	27-24-22-20
eCl@ss 9.0	27-24-22-20
ETIM 8.0	EC000237
ETIM 7.0	EC000237
PU (SPU)	1 Stück

Subject to changes. Please also observe the further product documentation!



Packaging type	bag
Country of origin	DE
GTIN	4045454765200
Customs tariff number	85444290900

Downloads

Documentation

Manual

System Manual WAGO I/O System 750 / 753 Decentralized Automation Technology	V 3.1.0 2022 May 11	pdf 8.7 MB	Download
--	------------------------	---------------	----------

Bid Text

750-923/000-001 docx - Datei	2019 Jun 26	docx 15.0 kB	Download
750-923/000-001 X81 - Datei	2019 Feb 19	xml 4.1 kB	Download

Tutorial

Set IP address with Ethernet Settings In this video we are demonstrating how you can set a IP address with Ethernet Settings. Content: 00:27 – Chapter #1 Download and install software; 00:56 – Chapter #2 Open Ethernet Settings; 01:10 – Chapter #3 Establish serial Connection; 01:34 – Chapter #4 Set IP address; 02:10 – Chapter #5 Check IP address	3.0 2017 Dec 18	mp4 88.3 MB	Download
---	--------------------	----------------	----------

System Description

750/753 Series I/O-System – General Product Information	pdf 1.7 MB	Download
---	---------------	----------

CAD/CAE-Data

CAE data

EPLAN Data Portal 750-923/000-001	URL	Download
WSCAD Universe 750-923/000-001	URL	Download
WSCAD Universe 750-923/000-001	URL	Download

FPI AN Data Portal 750-923/000-001

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Environmental Product Compliance 750-923/000-001

[URL](#)

[Download](#)

Device Files

Device Driver

WAGO USB Service Kabel Treiber / Serie 750 und 857

6.5.3.0

2014 Sep 10

zip

4.8 MB

[Download](#)

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 750-923/000-001

[URL](#)

[Download](#)

Configuration cable; USB connector; Length: 5 m

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169

Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.